




# MOBILE PORTAL & CANON PRINT BUSINESS APP

## SCENARIO

- Do you have a work smartphone or tablet in which you frequently access and send documents?
- Would you like a way to integrate your smartphone or tablet with your imageRUNNER ADVANCE MFP to be able to print and scan documents?

## BENEFITS

- Help improve convenience through integrating imageRUNNER ADVANCE devices with your smartphone or tablet
- Print from documents saved on your mobile device, sent to you in an email, or saved in your Google Drive account or Dropbox account.
- Improve efficiency through release and printing jobs waiting in your print queue from your mobile device as well as providing emails addresses saved in your smartphone/table contacts to be used as send destinations (third generation iR ADV only).



Initiate a **direct connection** with the MFP so users do not need to have their mobile device

# 9:12 AM Canon PRINT Busness President Provide Address Other Functions

#### Note:

Supported Models:

Third Generation imageRUNNER ADVANCE models

-Compatible with iPhone, iPad, and iTouch (Requires iOS 8.0 or later)


-Compatible with Android (Requires 4.0 or up)


-Bluetooth feature requires Connection Kit for BLE, NFC feature requires NFC Kit

-Requires Unified Firmware Platform version 3.3 or higher

-Canon PRINT Business features are not available on systems configured with imagePASS or ColorPASS controller

## At the imageRUNNER ADVANCE Control Panel






#### Note:


• Administrator level login required to make changes in Settings/Registration.

- You may be required to reset the device upon changing settings.
- Only need to complete these two steps once. If you are re-connecting, skip to Step 3.

## At the imageRUNNER ADVANCE Control Panel







Note: This screen will indicate if Bluetooth or NFC is available. Enable these the same way.

## On your smartphone or tablet:

<b>♀</b> 9:09		1	•••••		91%	••••0		91% 💷)	
Canon Busin			$\times$	Select Printer	Edit	$\times$	QR Code		
	• N/A		CUSA-30     CUSA-30			Scan the QR code.			
iR-ADV C5560 Direct Connection			Auto Sear (Wi-Fi)	rch	>				
		Ι.	Manual Se (Wi-Fi)	earch	>	]	- ,- Bluete		
Docun	nents	→	QR Code		→	• [	<b>1 1 1 1 1 1 1 1 1 1</b>		
	0		Nearby Pr	rinters	>				
Scan	Capture								
Direct Connec	tion						7		
Release and Print			Line up the QR Code				Direct Connect	. Info.	
Provide Address			with the green frame on your						
Other Functions			smartphone or tablet camera						

### On your smartphone or tablet:


Via Blueto	<b>Oth</b> (iOS only; Req	uires Connecti	ion Kit for Bluei	tooth LE)			
••••• $\widehat{>}$ 9:09 AM	91% 💶 🕅	••••○ 🔶	11:45 AM earby Printers	∦ 78% <b>■</b> D•	••••od	≎ 11:46 AM Usage	∦ 78% 💶)
(E.)	• N/A	Bluetooth		ALC: NO		$\bigcirc$	
iR-ADV C5 Direct Conner		Search using E Wi-Fi.	Bluetooth and conne	ect with			
Direct Connex		iR-ADV C	EEEO	_			
<u> </u>		IR-ADV C	5550		Follow	the steps below:	
Documen	ts	1				the steps below.	m the Main
					Menu o	f the printer.	
Scan	Capture				2. Tap	[Continue] on this	screen.
Direct Connection							
Release and Print						$\mathbf{i}$	
Provide Address						7	
Other Functions		Adjust Sensi	tivity	>			
						ancel	Continue
		Then	select [Add	d]			
🔊 Mobile Portal			-	¢ 📃	••••	গ 11:46 AM Usage	<b>\$</b> 78% <b>■</b> D•
Connect to this device from Access Point Mode is availab	he device you want to connect. le.			?			
LAN Connection	Direct Connection		-¦- Bluetoot	th			
= SSID					"iR-	Iuetooth Pairing Red ADV C5550" would like to r iPhone. Enter the code s	pair with
► iR- Conner Device	t to this device from the device you Name: iR-ADV C5550 de: 019765	I want to connect.				"iR-ADV C5550".	
■ Network					Folk	Cancel P	air
= Devic			_		1. Se	the printer.	
► iR-		ОК	. Info.		2. Tap [C		reen.
	Disable						
					1	<b>2</b> ABC	3 Def
Waiting for Bluetooth	connection Open the Mobile Por	tal screen	tog Out		<b>4</b> <sub>бні</sub>	5 JKL	6 <sup>MNO</sup>
					7	Q	Q

# Enter the PIN Code displayed at the iR ADV screen into your smartphone or tablet

(This PIN can be customized in Settings/Registration. By default, it auto-generates a new PIN each time) 0


 $\langle \times \rangle$ 

#### For iPhone and iPad users only (skip to next page if using an Android device)



#### Paste the password (QR Code copied it to your clipboard)

#### You are now connected




#### Note:

Next time, you won't have to do the QR code because the phone will remember the ad hoc connection. Simply enable direct connection at the device and then select the hotspot from your Wi-Fi settings.



### On your smartphone or tablet:





# IN ENVIRONMENTS WITH AUTHENTICATION

## On your smartphone or tablet:

▲ 🗟 🏚 🛛 ♀ ३ ⊕ ♥ ∠ / 320 ⊖ <sup>+</sup> Canon PRINT Ξ	'w 12:42 PM 80% ■)	
iR-ADV C5560	App Settings	
LAN Connection	P Help	
Scan Capture	Information	
Release and Print		
Provide Address      Other Functions		
••••• * 12:42 PM 80%	••••• 12:42 PM 80% D Cancel User Information Done	1
App Settings  Send To		
Save Image To	Enter the user information for logging in to the printer.	
WebDAV Port	Log in as Guest user	
SNMP Settings	User Name:	Enter Username and password
public Vser Information	Joe Password:	information
Provide Address	•••	
On Menu Tip	Domain Name:	
	Use the same user information when printing	