

Canon imagePROGRAF: Print Driver Settings from a Mac

Using the Wide Format Print Driver to print from a MacOS 13 and up.

<ol style="list-style-type: none"> 1. File → Print 2. Select desired printer. 3. Change Paper Size to the size of the document. 	
<ol style="list-style-type: none"> 4. Several options will be listed for Paper Size. <ul style="list-style-type: none"> • Scroll to bottom of list to create a custom size by selecting Manage Custom Size. 	
<ol style="list-style-type: none"> 5. Presets can be created for quick settings selection: <ul style="list-style-type: none"> • Saved presets will be listed under Presets. • To save a preset, set the print settings up and click Save Current Settings as Preset... 	

<ul style="list-style-type: none"> Name the preset. Available For: Choose if the preset is to be shared with ALL printers, or just this one. Since this is a wide format, usually just for this one. 	<p>Preset Name: <input type="text" value="24x36 Blueprint"/></p> <p>Available For: <input checked="" type="radio"/> Mac Demo: IPF TX-3100 <input type="radio"/> All printers</p> <p>Type: <input type="radio"/> Custom Preset <input checked="" type="radio"/> Print Job Preset</p> <p style="text-align: right;"><input type="button" value="Cancel"/> <input type="button" value="OK"/></p>
<p>6. Printing Properties: (details below)</p> <ul style="list-style-type: none"> Preview Layout Paper Handling Printer Options Printer Info 	<p>> Preview Auto Rotate: On, Show Notes: Off, Scale Mode: Scale to Fit, Scale to Fit Mode: Print Entire Image</p> <p>> Layout 1 page per sheet</p> <p>> Paper Handling Collate Sheets, All Sheets</p> <p>> Printer Options</p> <p>> Printer Info</p>
<p>7. Preview:</p> <ul style="list-style-type: none"> Auto Rotate Scale: Select to manually adjust scale Scale to Fit <ul style="list-style-type: none"> Print entire image Fill entire paper Copies per page 	<p>Preview</p> <p><input checked="" type="checkbox"/> Auto Rotate <input type="checkbox"/> Show Notes</p> <p><input type="radio"/> Scale: 99%</p> <p><input checked="" type="radio"/> Scale to Fit: <input checked="" type="radio"/> Print Entire Image <input type="radio"/> Fill Entire Paper</p> <p>Copies per page: <input type="text" value="1"/></p>
<p>8. Layout:</p> <ul style="list-style-type: none"> Pages per Sheet Layout Direction Border Reverse Page Orientation Flip Horizontally 	<p>Layout</p> <p>Pages per Sheet: 1</p> <p>Layout Direction: <input type="button" value="Z"/> <input type="button" value="S"/> <input type="button" value="N"/> <input type="button" value="N"/></p> <p>Border: None</p> <p>Reverse Page Orientation: <input type="checkbox"/></p> <p>Flip Horizontally: <input type="checkbox"/></p>
<p>9. Paper Handling:</p> <ul style="list-style-type: none"> Collate Sheets Sheets to Print Sheet Order Scale to Fit Paper Size <ul style="list-style-type: none"> Destination Paper Size Scale Down Only 	<p>Paper Handling</p> <p>Collate Sheets: <input checked="" type="checkbox"/></p> <p>Sheets to Print: All Sheets</p> <p>Sheet Order: Automatic</p> <p>Scale to Fit Paper Size: <input checked="" type="checkbox"/></p> <p>Destination Paper Size: ARCH D 24.00 by 36.00 inches</p> <p>Scale Down Only: <input type="checkbox"/></p>

10. Printer Options:

- Color Matching
- Quality & Media
- Color Options
- Advanced Paper Settings
- Page Processing
- Additional Settings

Printer Options

- Color Matching ⓘ
- Quality & Media ⓘ
- Color Options ⓘ
- Advanced Paper Settings ⓘ
- Page Processing ⓘ
- Additional Settings ⓘ

Quality and Media:

- Media Type
- Paper Source
- Print Priority
- Print Quality
- Color Mode
- Rendering Intent
- Print Preview

Media Type: Auto (Use Printer Settings) ⌵

Paper Source: Roll Paper (Auto) ⌵

Print Priority: Auto (Use Printer Settings) ⌵

Print Quality: Standard ⌵

Color Mode: Color ⌵

Rendering Intent: Perceptual (Photo) ⌵

Print Preview



Cancel

OK

Color Options:

- **Color** can be strengthened & **Brightness** and **Contrast** can be adjusted from -5- to 50 here



View Color Pattern

Cyan: 0 [Slider: Low to High]

Magenta: 0 [Slider: Low to High]

Yellow: 0 [Slider: Low to High]

Brightness: 0 [Slider: Dark to Light]

Contrast: 0 [Slider: Low to High]



Cancel

OK

Advanced Paper Settings:

- Dry Time (Between Pages)
 - Time interval between print and cut/exit
- Dry Time (Between Scans)
 - Time interval between printing each scan (*prevents ink bleeding on a page or uneven coloring during borderless printing*)
- Roll Paper Safety Margin
 - Specify length of margins on the edges of the paper to make curled paper absorb the platen (*extremely curled paper will need*

Dry Time (Between Pages): Printer Default ⌵

Dry Time (Between Scans): Printer Default ⌵

Roll Paper Safety Margin: Printer Default ⌵

Cut Speed: Printer Default ⌵



Automatic Cutting: Yes ⌵

Unidirectional Printing



Cancel

OK

<p><i>the 20mm – uncurled paper will need printer default or 3mm)</i></p> <ul style="list-style-type: none"> • Cut Speed: <ul style="list-style-type: none"> ○ Printer Default ○ Fast: if clean cut surfaces are not possible with the standard setting ○ Standard: no problems with automatic cutting ○ Slow: use for adhesive paper; prevents glue from sticking to cutter • Automatic Cutting: <ul style="list-style-type: none"> ○ Yes, None, Print Cut Guideline • Unidirectional Printing: <ul style="list-style-type: none"> ○ Suppresses uneven coloring and line shifts during printing 	
<p>Page Processing:</p> <ul style="list-style-type: none"> • Roll Paper Width <ul style="list-style-type: none"> ○ Width: specify when custom size is chosen • 3-sided Borderless: <ul style="list-style-type: none"> ○ If checked and width or length of the output paper size is smaller than the roll width, a margin will be created on the right of the document, and the remaining three sides (<i>top, bottom, and left</i>) will be borderless • Banner Printing: <ul style="list-style-type: none"> ○ Print documents with multiple pages as one continuous document (<i>the spaces between the pages will be removed</i>) • Fit Roll Paper Width: <ul style="list-style-type: none"> ○ Printer expands/reduces the document to match the roll paper width and prints • No Spaces at Top or Bottom: <ul style="list-style-type: none"> ○ Gets rid of margins between prints • Rotate Page 90 degrees: <ul style="list-style-type: none"> ○ Save paper by rotating print by 90 degrees (<i>it will not rotate if print doesn't fit</i>) • Borderless Extension: <ul style="list-style-type: none"> ○ Adjust how much the document extends outside the paper by using the Borderless Extension slider bar • Print Centered: 	 <p>Roll Paper Width: 24 in Roll (609.6mm)</p> <p>Width: 24.02 inch (6.00-36.10)</p> <p><input type="checkbox"/> Three-sided Borderless</p> <p><input type="checkbox"/> Banner Printing</p> <p>Fit Roll Paper Width: Off</p> <p><input type="checkbox"/> No Spaces at Top or Bottom</p> <p><input type="checkbox"/> Rotate Page 90 degrees</p> <p>Borderless Extension: </p> <p><input type="checkbox"/> Print Centered</p> <p>Cancel OK</p>

<ul style="list-style-type: none"> ○ Prints in center of paper (<i>prints are normally right justified</i>) 							
<p>Additional Settings:</p> <ul style="list-style-type: none"> ● Output Method: <ul style="list-style-type: none"> ○ Set PIN for Printing: set a pin to release at the printer with it (<i>1-7 digits</i>) ○ Print after reception is complete: printing will start after the print job is received; it prevents a decrease in print quality due to the printing being suspended ● Save in Job Box: <ul style="list-style-type: none"> ○ Save the print job at the printer ○ Document Title: this will be the name of the job in the Job Box; it can stay the file name or be named differently ○ Job Box No.: select box number to be saved in 	<p>Output Method:</p> <p><input checked="" type="radio"/> Print</p> <p><input type="checkbox"/> Set PIN for printing PIN: _____ (1-9999999)</p> <p><input type="checkbox"/> Print after reception is complete</p> <p><input type="radio"/> Save in Job Box</p> <p>Document Title: <input type="text" value="Blank 24x36 file.pdf"/></p> <p>Job Box No.: <input type="text" value="1"/></p> <p><input type="button" value="Cancel"/> <input type="button" value="OK"/></p> <p><input checked="" type="radio"/> Save in Job Box</p> <p>Document Title: <input type="text" value="Test 1"/></p> <p>Job Box No.: <input type="text" value="3"/></p>						
<p>11. Printer Info:</p> <ul style="list-style-type: none"> ● Name, Location & Model ● Supply levels will show if 2-way communication is turned on 	<p>Printer Info</p> <table border="1"> <tr> <td>Name</td> <td>Mac Demo: IPF TX-3100</td> </tr> <tr> <td>Location</td> <td>172.29.70.111</td> </tr> <tr> <td>Model</td> <td>Canon TX-3100</td> </tr> </table> <p>Supply Levels</p> <p>Mbk: </p> <p>Bk: </p> <p>Y: </p> <p>M: </p> <p>C: </p> <p>Mc: </p> <p>Supply levels shown are approximate. Last updated today at 12:37 PM</p>	Name	Mac Demo: IPF TX-3100	Location	172.29.70.111	Model	Canon TX-3100
Name	Mac Demo: IPF TX-3100						
Location	172.29.70.111						
Model	Canon TX-3100						
<p>Once all selections have been made, select OK → Print</p>							

Reference: Canon : imagePROGRAF Manuals : TX-4100 TX-3100 TX-2100 TX-5410 TX-5310 TX-5210 : macOS Printer Driver. (n.d.). <https://ij.manual.canon/ij/webmanual/PrinterDriver/M/TX-4100/1.0/EN/PPG/dg-print4.html>