



## Xerox: Loading a Mac Print Driver

1. Search for [www.support.xerox.com](http://www.support.xerox.com) in the preferred web browser.
2. Search for the model of the Xerox device.
3. Select the link for printer drivers & downloads.





4. Select the mac driver to download and select download. If prompted, select whether there is a Built-in Controller (no Fiery) or a Server Powered by Fiery.
5. Open the downloaded file and open the office folder. Select the installer and run the installer.
6. Follow the steps in the wizard and log in when prompted.
7. Select the computer icon and type in the IPv4 address. Press Continue.
  - For AltaLink and VersaLink, the IP address will be in the top left corner of the home screen.
  - For WorkCentre and PrimeLink, press the Machine Status button and the IP address will be listed.
8. The wizard will show the completion if successful. Check the box to set as default and to print a test page and press Continue.
9. Press Close and Move to Trash. If the wizard did not find the machine, continue to the steps on following page.



## QUICK GUIDE

# LOFFLER

10. Open System Preferences.
11. Press **Printers & Scanners**.
12. Select the **+** sign to add a printer.
13. Select **IP** and enter the IP address.
14. Set the Protocol line to **Line Printer Daemon** and type **print** into the Queue line.
15. Name the printer.
16. In the Use line, select the drop down and press **Select Software...**
17. Type in the model in the search menu.
18. Press **OK**.
19. Press **Add**.
20. Select Options and Supplies.
21. Select Options.
22. Enter the machine's additional options and press **OK** to save.



**\*\*Note:** Print drivers are set to 2-sided and color by default. For assistance changing default settings, please contact the Loffler service department. Contact information is located on the red sticker on the front of the device.

